



OXYMAK

GERMAN TECHNOLOGY TURKISH MANUFACTURING



THROUGH  
QUALITY

<b>Generator Model</b>	Product Code O-500
Desing pressure	11 bar
Operating pressure	7 bar
Net weight	2800 kg
Noise level	55 max 85 dB (A)
Ambient temperature	+5 to +40 °C
Electrical connection	220V 50-60 Hz 220V 50Hz
Power consumption	150 W
Safety class	54 IP
Temperature	20 °C
Above Sea Level	0 m
Pressure	1. 0133 bar
Humidity	70 %
Inlet Filtration	0.01 micron
Inlet Filtration * (ACfilter)	0.003 micron
Outlet Filtration	3 bis 5 micron
Dimension	1260x2150x2780 LxWxH (mm)

<b>Oxygen Purity</b>	<b>90%</b>	<b>93%</b>	<b>94%</b>	<b>95%</b>	<b>99%</b>
Capacity (Nm3/h)	40,6	36,9	35,3	33,6	Optional
Compressed air factor	11	11	11	11	Optional
Compressed air (Nm3/h)	446,60	405,9	388,3	369,6	Optional
Compressed air (m3/h)	479,3	435,6	416,7	396,7	Optional
Product vessel (l)	1.500	1.500	1.500	1.500	Optional
Compressed air vessel (l)	3.000	3.000	3.000	3.000	Optional
Compressed air inlet	1 ½"	1 ½"	1 ½"	1 ½"	1 ½"
Connection O2 output	1"	1"	1"	1"	1"

### Generator Specification

PSA Oxygen Generators separate oxygen from pressurised air.

The composition of the product is determined by measuring the residual oxygen content.

The oxygen content is calculated by subtracting the residual oxygen content from 100 %.

Air is composed of nitrogen (78.1%), oxygen (20.9 %), Argon (0.9 %), CO2 (0.03 %), and some inert gases

### Compressed air specification

Dew point +3 °C, Air quality:according to ISO 8573.1, class 1 solid particulates and oil class 4 humidity,

free of all contamination (free of ozone)

### Touch Control Panel

<b>Standard</b>	<b>Option</b>
4" Colorless	7" Color Touch Monitor
Inlet Filters 0.01 micron	Inlet temperature
Outlet filter 5-3 micron	Inlet dew point
4 different languages	Outlet dew point
Operational status	Flow meter
Outlet flow regulator	Outlet pressure
Inlet-Outlet pressure regulator	Oxygen analyzer

### Material

Outside protection,Piping,Valves,powder paint coated

stainless steel or galvanized steel,stainless steel AISI 316 LPA actuator